## **Contact Us**

### Toll-Free: 877-771-6970

Customer Service: Press "1" Technical Support: Press "2" Repair Department: Press "4" Shipping Department: Press "5" Accounting: Press "6"

Business Hours: Monday – Friday 8:00 am – 4:00 pm EST

### **Factory Address:**

Power Vac Corporation, Inc. 4811 NE 12<sup>th</sup> Avenue Oakland Park, FL 33334

E-mail: CustomerService@PowerVacCorporation.com Website: www.PowerVacCorporation.com



Visit our website to find a distributor in your area. POWER VAC CORPORTATION DOES NOT SELL TO THE PUBLIC.











# **Owner's Manual**




Startup guide & instructions inside 🗲


# **Start Up Guide**

Engineering Specifications2
Battery and Charger Info3
Install Your Battery4
Installing Your Charge Plug4
Assembling Your Filter Bags5
Equipment Maintenance6-7
Male & Female Plug Installation8
Troubleshooting9
Repair Services10
Warranty Info10
Caring For Your Service Cart11
Purchasing Replacement Parts12
Parts List for PV210013
Parts List for PV220014
Parts List for PV250015
Parts List for PV300016
Parts List for Large Service Cart17
Parts List for Mini Cart18
Contact UsBack Page

## **Parts List for Mini Cart**



### **Parts List for Large Cart**



# **Engineering Specifications**

All Power Vac vacuums and carts are proudly manufactured in America. We also support American vendors by purchasing items within the United States.



- Both the PV2100 & PV2500 have a have a 6" throat. These vacuums have a 20" x 11" cleaning path and pump approximately 14,000 gallons per hour. Includes a 40' or 60' floating power cord. They are recommended for residential pools and fountains.
- The PV2200 has an 8" throat. This vacuum has a 20" x 11" cleaning path and pumps approximately 16,000 gallons per hour. It also includes a 40' or 60' floating power cord. This vacuum is recommended for residential and commercial use. It is highly recommended that this vacuum be purchased with a large cart (item# 040-D-40 or 040-D-60).
- The PV3000 has an 8" throat. This vacuum has a 40" x 11" cleaning path and pumps approximately 16,000 gallons per hour. Includes a 75' floating power cord. This vacuum is recommended for water parks and resorts. It is highly recommended to be purchased with the mini cart (item# 003000-D-S).
- All vacuums have a 30 pound thrust motor and a custom cut 2-blade, no clog propeller, designed to pick up heavy debris.
- A custom-designed aluminum handle for your telescopic pole comes standard with every vacuum
- A safety lid comes standard on all vacuums. This important little flap traps debris inside the filter bag once the vacuum shuts off, preventing it from flowing back out. It also protects your hands from the spinning propeller.
- Ergonomic battery case with built-in fuse allows battery to shut off, preventing overheating.
- A charging plug comes standard with all units. This plug attaches to your battery charger for quicker use. See page 4 for installation directions. Page 2

# **Battery & Charger Info**

### **AVAILABLE AT A SPECIALTY BATTERY STORE NEAR YOU**

ANY BRAND BATTERY WITH THESE SAME SPECIFICATIONS WILL WORK FOR YOUR VACUUM



#### FOR PORTABLE USE

12V 35AH ABSORBED GLASS MAT (AGM) BATTERY

WERKER® MANUFACTURER ITEM # WKA12-35C WEIGHT: 27 LBS RUN TIME APPROX: 3 HOURS (PV2100 & PV2500) 12V 6 AMP OR 12V 10 AMP CHARGE ONLY



#### FOR MINI SERVICE CART DEEP CYCLE 12V 55AH AGM BATTERY W/P TERMINAL

WERKER® MANUFACTURER ITEM #WKDC12-55P WEIGHT: 42 LBS RUN TIME APPROX: 4 - 4.5 HOURS (PV2100 & PV2500) 2 - 2.5 HOURS (PV2200 & PV3000) 12V 6 AMP OR 12V 10 AMP CHARGE ONLY



### FOR LARGE SERVICE CART

DEEP CYCLE 12V 55AH - 100AH AGM BATTERY W/ P TERMINAL

WERKER® MANUFACTURER ITEM #WKDC12-100P WEIGHT: 74 LBS RUN TIME APROX: 7.5 - 8 HOURS (PV2100 & PV2500) 5 HOURS (PV2200) 12V 6 AMP OR 12V 10 AMP CHARGE ONLY



LARGE CART BATTERY BOX PART #12-A-D

FOR CHARGING BATTERY USE ANY CHARGER WITH AUTOMATIC SHUT-OFF 12V 6 AMP OR 12V 10 AMP CHARGE ONLY



CONTACT YOUR DISTRIBUTOR TO ORDER A BATTERY BOX POWER VAC® DOES NOT SELL BATTERIES OR BATTERY CHARGERS POWER VAC CORPORATION® IS NOT AFFILIATED OR PARTNERED WITH WERKEN® BRAND . WE SUGGEST WERKER® BRAND BATTERIES DUE TO THEIR QUALITY AND FACTORY TESTING ANY BRAND BATTERY WITH THE SAME SPECIFICATIONS WILL WORK FOR YOUR VACUUM

#### WARNING!

BATTERIES CONTAIN SULFURIC ACID WHICH CAN CAUSE SEVERE BURNS. AVOID CONTACT WITH SKIN, EYES, AND CLOTHING, BATTERY ACID PRODUCES HYDROGEN AND OXYGEN GASES WHEN BEING CHARGED. THE EXPLOSIVE GAS ESCAPES THROUGH THE FILL/VENT CELL CAPS AND MAY FORM AN EXPLOSIVE ATMOSPHERE AROUND THE BATTERY IF VENTILATION IS POOR. THIS GAS MAY REMAIN AROUND THE BATTERY FOR SEVERAL HOURS AFTER IT HAS BEEN CHARGED. SPARKS OF FLAMES CAN IGNITE THE GAS AND CAUSE AN EXPLOSION WHICH MAY SHATTER THE BATTERY AND CAUSE BLINDNESS OR OTHER SERIOUS INJURY. ALWAYS CHARGE BATTERIES IN AN OPEN AIR AREA TO LOWER THE RISK OF A FIRE OR EXPLOSION. NEVER CHARGE BATTERY ON A SETTING HIGHER THAN TEN (10) AMPS. IF BATTERY USE REQUIRES WATER CHECK IT BEFORE CHARGING THE BATTERY.


## Parts List for PV3000

)5-D-75 _ 75' flo	bating power cord-A	clamp
108-D	compression fitting B	ale power plug
100 0 _		
	017-D_safety lid O	aluminum handle brack
016-		_3000 base
)-R set of 8 whe		aluminum handle
		a.
		7
PART #	DISCRIPTION PV3000	
003000-D-Н	PV3000 Vacuum Only 75' Floating Power Cord & 2 Filter Bags	
003000-D-S	PV3000 Vacuum 75' Floating Power Cord With Mini Cart & 2 Filter Bags	
	REPLACEMENT PARTS	
004-D	Cord Float (For Non-Floating Cord-Purchsed Before 2010)	
005-D-75	75' Blue Thick Gauge Floating Power Cord W/ Brass + Male Plug (customer install voids warranty)	<u>A</u>
006-D-3000	Motor 30Lb Thrust For PV3000 (customer install voids warranty)	
007-D	"C"-Clamp	6
009-B-D	Aluminum Handle	•
010-D	Female Plug (On Battery Case)	
011-D	Male Plug (On End Of Power Cord)	G
013-D-R	PV3000 Replacement Base-Shell W/ Wheels, Handle, Handle Bracket & Safety Lid	0
015-B-D	Aluminum Handle Bracket (Horizontal) For Units Purchased Before 2006	0
016-D	Carrying Handle	O
017-D	PV2200/3000 Safety Lid	C
026-D-R	Set Of 8 Wheels (2 Fixed/6 Swivel)	e
027-D	Single Swivel Caster Wheel	
027-D-A	Single Fixed Wheel	
029-D	Nut & Pin For Prop	
030-D-3000	Twin Blade Propeller (Prop) For PV3000	
058-D	Brass Nut For Motor (Tightens Motor To Shell)	
081-D	Orange Cord Seal Gromet (Inside Compression Fitting)	
092-D	Single PV Female Connector For Motor	
093-D	Single PV Male Connector For Power Cord	
108-D	Brass Compression Bell For Floating Power Cord (Connects Cord To Motor)	B
	FILTER BAGS	
019-D-2200	26" Super fine mesh filter bag (Debris Pick up: Fine Sand & Leaves)	
020-D-2200	26" Micron filter bag (Debris Pick up: Light Debris down to 15 Microns)	
022-D-2200	26" Heavy duty mesh filter bag (Debris Pick up: Sand, Leaves, Rocks & Glass)	
022-D-2200L	42" Heavy duty mesh filter bag (Debris Pick up: Sand, Leaves, Rocks & Glass)	
023-D-2200	26" Screen mesh filter bag (Debris Pick up: Large Leaves & Small Sticks)	
023-D-2200L	42" Screen mesh filter bag (Debris Pick up: Large Leaves & Small Sticks)	


	Parts List for PV25	00
05-D-40 40'	floating power cord	07-D_c-clamp
		11-D_male power plug
		15-A-D_nylon handle bracket
026-D		09-B-D_aluminum handle
		13-D-A _2100 base
	PORTABLE VERSIONS	
003-D-40	PORTABLE VERSIONS PV2500 Vacuum W/ 40' Floating Power Cord With Battery Case & 2 Filter Bags	
003-D-40	PV2500 Vacuum W/ 40 Floating Power Cord With Battery Case & 2 Filter Bags	
003-D-80	CARTED VERSIONS	
114 D 40		
114-D-40	PV2500 Vacuum 40 ' Cord & Svc Cart With Truck/Trailer Mount & Hitch	
114-D-60 114-40-F-D	PV2500 Vacuum 60 ' Cord & Svc Cart With Truck/Trailer Mount & Hitch PV2500 Vacuum 40 ' Cord & Svc Cart Without Truck/Trailer Mount & Hitch	
114-40-F-D 114-60-F-D	PV/2500 Vacuum 40° Cord & Svc Cart Without Truck/Trailer Mount & Hitch PV/2500 Vacuum 60° Cord & Svc Cart Without Truck/Trailer Mount & Hitch	
114-00-F-D	PV2500 Vacuum 60° Cord & Sve Cart Without Truck/Trailer Mount & Hitch REPLACEMENT PARTS	
004-D	Cord Float (For Non-Floating Cord-Purchsed Before 2010)	
004-D 005-D-40	40' Blue Floating Power Cord W/ Brass + Molded Male Plug (customerinstall voids wai	manth/
005-D-40 005-D-60	40 Blue Floating Power Cord W/ Brass + Molded Male Plug (customer install volds wai 60' Blue Floating Power Cord W/ Brass + Molded Male Plug (customer install volds wan	
005-D-60 006-D-2500	60 Blue Floating Power Cord W/ Brass + Molded Male Plug (customer install volds warn Motor 30Lb Thrust For PV2100 (customer install volds warranty)	any, w
006-D-2500	"C"-Clamp	Ê
009-A-D	Chrome Handle With Delron Clip	•
009-B-D	Aluminum Handle	0
009-C-D	Chrome Swivel Handle	W
010-D	Female Plug (On Battery Case)	
010-B-D	Female Plug W/ Fuse Attachment For Battery Case	
011-D	Male Plug (On End Of Power Cord)	6
012-D	Portable Battery Carrying Case W/ Built In Fuse	
013-D-F	Pv2500 Replacement Base-Shell W/ Wheels, Handle, Handle Bracket & Safety Lid	0
013-D-F-S	Pv2500 Replacement Base-Shell Only	
015-A-D	Nylon Handle Bracket (Vertical)	G
015-B-D	Aluminum Handle Bracket (Horizontal) For Units Purchased Before 2006	
016-D	Carrying Handle	C
026-D	Set Of 4 Caster Wheels	Ō
027-D	Single Swivel Caster Wheel	
027-D-A	Single Fixed Wheel	
029-D	Nut & Pin For Prop	
030-D-2500	Twin Blade Propeller (Prop) For PV2500	
058-D	Brass Nut For Motor (Tightens Motor To Shell)	
081-D	Orange Cord Seal Gromet (Inside Compression Fitting)	
085-D	Steering Kit (2 Fixed/2 Swivel Wheels & Chrome Swivel Handle)	
092-D	Single PV Female Connector For Motor	
093-D	Single PV Male Connector For Power Cord	
108-D	Brass Compression Bell For Floating Power Cord (Connects Cord To Motor)	B
116-D	Portable battery box replacement strap + grip	
	FILTER BAGS	
019-D-2100	26" Super fine mesh filter bag (Debris Pick up: Fine Sand & Leaves)	
019-D-2500	15" Super fine mesh filter bag (Debris Pick up: Fine Sand & Leaves)	
020-D-2100	26" Micron filter bag (Debris Pick up: Light Debris down to 15 Microns)	
022-D-2100	26" Heavy duty mesh filter bag (Debris Pick up: Sand, Leaves, Rocks & Glass)	
022-D-2100L	42" Heavy duty mesh filter bag (Debris Pick up: Sand, Leaves, Rocks & Glass)	
and D offer	15" Heavy duty mesh filter bag (Debris Pick Up: Sand, Leaves, Rocks & Glass)	
022-D-2500 023-D-2100 023-D-2100L	26" Screen mesh filter bag (Debris Pick up: Large Leaves & Small Sticks) 42" Screen mesh filter bag (Debris Pick up: Large Leaves & Small Sticks)	

### **Install Your Battery**

- 1. Place your 12 volt battery inside the battery carrying case (this may have come with your vacuum purchase).
- 2. Take the plug wires-connect the red [+] to the positive [+] post of the battery.
- 3. Connect the black [-] wire to the negative [-] post of the battery.



### **Installing the Charge Plug**




This plug is included in with the purchase of a new vacuum. Here is how to charge your battery hassle-free, without taking the lid off the battery case. Installing the charge plug is optional.

- 1. Cut the clamp ends off of your charger.
- 2. Strip back the wires exposing about 1". See fig. 1.
- Connect the positive wire of the charger to the positive [+] wire of the charge plug. Do the same for the negative [-] black wire. Clamp the wires into the butt connector. See Fig 2.
- 4. Apply heat to the butt connectors until it shrinks slightly and adheres to the wires

## **Assemble Your Filter Bags**

### Instructions



- 1. Feed bungee cord thru one opening of top seam
- 2. Push bungee all the way thru, until both rubber ends are exposed
- 3. Take both ends of bungee and line them up evenly
- 4. Measure 1 inch below rubber ends and use black zip tie to bring two ends together
- 5. Pull zip tie as tight as possible. Cut away the excess zip tie.
- 6. Turn bag inside out (seam goes on inside)

Once assembled, slip filter bag over top opening of vacuum. The bag will collect debris from water as vacuum operates. Empty the filter bag of all debris when it becomes full. These bags generally need to be replaces every 3-4 months (with standard use).



See parts lists for item numbers.

Power Vac bags filter a wide variety of pool debris. Choose which one works for you:

	Fine Sand	Sand	Leaves	Twigs	Glass	Algae	Hair	Diatomaceous Earth
Screen			•	•		•		
Heavy Duty		•	٠	•	٠			
Super Fine	•	•	٠	•			•	
Micron	•						•	•

## Parts List for PV2200

	floating power cord floating power cord floating power cord floating power cord @ 011-D_male	
108-	D_compression fitting	on handle bracket
		uminum handle
026-L	o_swivel caster wheels  □ \	200 base
PART #	DISCRIPTION PV2200	
	VACUUM ONLY – DESIGNED TO WORK WITH LARGE SVC CART	
001-D-40	PV2200 Vacuum 40' floating power cord (vacuum only)	
001-D-60	PV2200 Vacuum 60' floating power cord (vacuum only)	
001-D-75	PV2200 Vacuum 75' floating power cord (vacuum only)	
	CARTED VERSIONS	
040-D-40	PV2200 Vacuum 40 ' cord & svc cart with truck/trailer mount & hitch	
040-D-60	PV2200 Vacuum 60 ' cord & svc cart with truck/trailer mount & hitch	
040-40-A-D	PV2200 Vacuum 40 ' cord & svc cart without truck/trailer mount & hitch	
040-60-A-D	Pv2200 vacuum 60 'cord's sec cart without truck/trailer mount & hitch	
040-00-412	REPLACEMENT PARTS	
004-D	Cord Float (For Non-Floating Cord-Purchsed Before 2010)	
004-D 005-D-40	40' Blue Floating Power Cord W/ Brass + Molded Male Plug (customerinstall wids warranty)	A
005-D-40	60' Blue Floating Power Cord W/ Brass + Molded Male Plug (customer install voids warranty)	Ä
005-D-80	75' Blue Floating Power Cord W/ Brass + Wolded Wate Flug (customer install voids warranty)	
006-D-2200		W
008-D-2200 007-D	Motor 30Lb Thrust For PV2200 (customer install voids warranty) "C"-Clamp	6
009-A-D 009-B-D	Chrome Handle With Delron Clip Aluminum Handle	
009-D-D	Chrome Swivel Handle	
010-D	Female Plug (On Battery Case)	
011-D	Male Plug (On End Of Power Cord)	<u> </u>
013-D-C	PV2200 Replacement Base-Shell W/ Wheels, Handle, Handle Bracket & Safety Lid	
013-D-C-S	PV2200 Replacement Base-Shell Only	
015-A-D	Nylon Handle Bracket (Vertical)	<b>B</b>
015-B-D	Aluminum Handle Bracket (Horizontal) For Units Purchased Before 2006	
016-D	Carrying Handle	0
017-D	PV2200/3000 Safety Lid	0
026-D	Set Of 4 Caster Wheels	
027-D	Single Swivel Caster Wheel	
027-D-A	Single Fixed Wheel	
029-D	Nut & Pin For Prop	
030-D-2200	Twin Blade Propeller (Prop) For PV2200	
058-D	Brass Nut For Motor (Tightens Motor To Shell)	
081-D	Orange Cord Seal Gromet (Inside Compression Fitting)	
085-D	Steering Kit (2 Fixed/2 Swivel Wheels & Chrome Swivel Handle)	
092-D	Single PV Female Connector For Motor	
093-D	Single PV Male Connector For Power Cord	0
108-D	Brass Compression Bell For Floating Power Cord	B
010 B 000	FILTER BAGS	
019-D-2200	26" Super fine mesh filter bag (Debris Pick up: Fine Sand & Leaves)	
020-D-2200	26" Micron filter bag (Debris Pick up: Light Debris down to 15 Microns)	
022-D-2200	26" Heavy duty mesh filter bag (Debris Pick up: Sand, Leaves, Rocks & Glass)	
022-D-2200L	42" Heavy duty mesh filter bag (Debris Pick up: Sand, Leaves, Rocks & Glass)	
023-D-2200	26" Screen mesh filter bag (Debris Pick up: Large Leaves & Small Sticks)	
023-D-2200L	42" Screen mesh filter bag (Debris Pick up: Large Leaves & Small Sticks)	

	Parts List for PV2100	
005-D-4 005-D-6	40 _ 40' floating power cord 60 _ 60' floating power cord 108-D_ compression fitting B	er plug
	018-D_safetylid C 015-A-D_nylon h	
	016-D_carrying handle 0 009-B-D_aluminu	
	026-D_swivel caster wheels	ase
PART #		
174K1#	PORTABLE VERSIONS	
002-D-40	PV2100 Vacuum 40' floating power cord with battery case & 2 filter bags	
002-D-60	PV2100 Vacuum 60' floating power cord with battery case & 2 filter bags	
	CARTED VERSIONS	
039 <b>-D-</b> 40	PV2100 Vacuum 40 ' cord & svc cart with truck/trailer mount & hitch	
039-D-60	PV2100 Vacuum 60 ' cord & svc cart with truck/trailer mount & hitch	
039-40-A-D	PV2100 Vacuum 40 ' cord & svc cart without truck/trailer mount & hitch	
039-60-A-D	PV2100 Vacuum 60 'cord & svc cart without truck/trailer mount & hitch	
	REPLACEMENT PARTS	
004-D	Cord Float (for non-floating cord-purchsed before 2010)	
005-D-40	40' Blue floating power cord w/ brass + molded male plug (customer install voids warranty)	
005-D-60	60' Blue floating power cord w/ brass + molded male plug (customer install voids warranty)	
006-D-2100	Motor 30# Thrust for PV2100 (customerinstall voids warranty)	
007-D	C-Clamp 🕒	
009-A-D	Chrome Handle with Delron clip	
009-B-D	Aluminum Handle	
009-C-D	Chrome Swivel Handel	
010-D	Female Plug (on battery case)	
010-B-D	Female Plug w/ fuse attachment for battery case	
011-D	Male Plug (on end of power cord)	_
012-D	Portable battery carrying case with built in fuse	
013-D-A	PV2100 Vacuum Replacement Base w/wheels, handle bracket, handles & safety lid PV2100 Replacement Base-Shell Only	_
013-A-D-S	· · · · · · · · · · · · · · · · · · ·	
015-A-D 015-B-D	Nylon Handle Bracket (vertical)	_
015-B-D	Carrying Handle	
018-D	PV2100 Safety Lid	_
026-D	Set of Four Swivel Wheels	
027-D	Single Swivel Caster Wheel	
027-D-A	Single Fixed Wheel	
029-D	Nut and Pin (For Prop)	
030-D-2100	Twin blade propeller (prop) for PV2100	
058-D	Large Brass Nut (tightens motor to shell)	
081-D	Orange cord seal grommet (inside compression fitting)	
085-D	Steering Kit (2 Fixed/2 Swivel Wheels & Chrome Swivel Handle)	
092-D	Single PV female connector for motor	
093-D	Single PV male connector for power cord	
108-D	Brass compression bell for floating power cord (attached cord to motor)	
116-D	Portable battery box replacement strap + grip	
	FILTER BAGS	
019-D-2100	26" Super fine mesh filter bag (Debris Pick up: Fine Sand & Leaves)	
020-D-2100	26" Micron filter bag (Debris Pick up: Light Debris down to 15 Microns)	
022-D-2100	26" Heavy duty mesh filter bag (Debris Pick up: Sand, Leaves, Rocks & Glass)	
022-D-2100L	42" Heavy duty mesh filter bag (Debris Pick up: Sand, Leaves, Rocks & Glass)	
023-D-2100	28" Screen mesh filter bag (Debris Pick up: Large Leaves & Small Sticks)	
023-D-2100L	42" Screen mesh filter bag (Debris Pick up: Large Leaves & Small Sticks)	

## **Equipment Maintenance**

Important tips on keeping your vacuum in top shape:

1. CLEAN PROPELLER (PROP) REGULARLY. MAKE SURE YOUR

VACUUM IS UNPLUGGED. Unscrew the nut (see fig 1) and clear prop of any debris (see fig 2). If removing the pin inserted between the motor shaft make sure to replace it immediately. When screwing the nut back on to prop do not over tighten.

Failure to regularly clean prop may cause motor to lock up. In some cases the debris will make its way down into the motor armature. Do not put fingers near prop while motor is running! Serious injury may occur.





Figure 1

Figure 2

2. WRAP POWER CORD PROPERLY AFTER EVERY USE (see Fig 3). Keep power cord in good condition and free of kinks, to ensure optimal performance. Allowing your power cord to knot and kink may result in one or more areas on cord where power shortages occur.



### 3. DO NOT RUN THE VACUUM OUT OF WATER FOR MORE THAN 20

**SECONDS.** Our motors our designed to operate under water. Running the motor while out of water may cause motor to overheat.

4. **DO NOT PICK THE VACUUM UP BY THE CORD.** Use the white carrying handle on the side. Pulling on the power cord or picking vacuum up by power cord can jeopardize the water tight seals installed on cord and motor. When a leak occurs, motor can cease from water damage.

5. **KEEP CHARGING POST FREE OF CORROSION.** Properly caring for your battery will extend its life. Make sure to charge it daily.

6. IF YOU NOTICE A SIGNIFICANT DIFFERENCE IN PERFORMANCE OR APPEARANCE, IT IS HIGHLY RECOMMENDED TO REPLACE YOUR PARTS. It is important to keep your male and female plugs in top operating condition.

# **Purchasing Replacement Parts**

For your convenience all parts on your Power Vac equipment are replaceable. This will allow you to keep your vacuum in top working condition. It is recommended to replace all parts as needed for general maintenance to ensure your equipment's performance and longevity. For a full list of parts see pages 13-18

### POWER VAC CORPORATION DOES NOT SELL TO THE PUBLIC.

PLEASE VISIT OUR WEB SITE FOR A LIST OF DISTRIBUTORS TO PURCHASE FROM.



## **Caring For Your Service Cart**

1. Grease wheel bearings at least once a month using an industrial lubricant.

2. Rinse down cart at the end of every day. This will help prevent chemical erosion.


3. Store in a dry place out of the sun at the end of the day.

4. Check battery once a month for any acid leaks.

5. Look over male and female plug frequently for any sign of damage. Replace if needed.




**Male & Female Plug Installation** 



STEP 1. CUT AWAY OLD PLUG AND STRIP BACK POWER CORD, EXPOSING THE WIRES ABOUT ONE INCH (FIG.1)

- STEP 2. CONNECT THE WIRES OF YOUR NEW PLUG TO THE WIRES OF YOUR POWER CORD. CLAMP DOWN ON WIRE CONNECTORS (FIG.2)
- STEP 3. SLIP PIECE OF BLACK HEAT SHRINK TUBE OVER EXPOSED WIRE CONNECTIONS, POSITIONING ABOUT TWO INCHES DOWN FROM THE TIP OF THE PLUG. APPLY HEAT TO SHRINK TUBE UNTIL IT LOOKS LIKE FIG. 3, OR UNTIL ADHESIVE SEEPS SLIGHTLY OUT OF THE SIDES OF THE TUBE.

#### PORTABLE BATTERY CARRYING CASE OUTLET REPLACEMENT INSTRUCTIONS (FEMALE PLUG)



STEP 1. PLUG BOTH RED WIRES INTO FUSE. LOAD TO LOAD / LINE TO LINE

STEP 2. CONNECT BOTH RING TERMINALS TO BATTERY <u>RED[+]</u> TO <u>RED[+]</u> / <u>BLACK[-]</u> TO <u>BLACK[-]</u>

Page 8

# Troubleshooting

#### 1. My vacuum turns on but my propeller will not spin.

- MAKE SURE VACUUM IS UNPLUGGED. Unscrew the prop nut on the propeller, remove prop and clear any debris that may be wrapped around the motor shaft. This may be causing the motor to lock up.

# 2. The power goes on and off when I wiggle the plug in the battery outlet.

- Inspect the plug on your power cord. Is it in good condition? Good condition = no corrosion or burnt spots. With repeated use this plug can get worn out and cause power shortages to your vacuum. If your power cord plug is damaged in any way, it is recommended that you replace it.

#### 3. My vacuum will not run.

Make sure battery is charged and cord is plugged in all the way.
Has the fuse/breaker in your battery box popped? If so then press it in to reset.

Follow the directions in step 1 & 2.

- Inspect battery connectors for corrosion.

- If you have been picking up the vacuum by its cord, and not the provided carrying handle, the water tight seals inside the cord and motor are most likely taking on water. When this happens corrosion begins and the motor or cord can fail. At this point you will need to replace the damaged parts.

### Tech Support Help Line: 877-771-6970 PRESS "2"

Open Monday – Friday 8:00 am – 4:00 pm EST E-mail: TechSupport@PowerVacCorporation.com

# We Provide Repair Services

Power Vac provides an excellent repair service. We offer a turnaround time of 48 hours or less. No RMA's required. Just visit our website to fill out our **Repair Return Form**. Make sure to print it out and place the form inside with your vacuum and mail it to our factory (address is on form). Power Vac is not responsible for shipping charges requiring the product to get to our factory. When the package is received a technician will contact you to discuss the needed repairs.

Keep in mind that Power Vac cannot warranty do-it-yourself installations. To receive a warranty on a motor or cord it will have to be installed by a certified Power Vac technician.

If your vacuum is still under warranty you will not be charged for repairs done to your motor, cord or shell. Power Vac will also pay to have the vacuum shipped back to you.

# Warranty Info

All Power Vac vacuums come with a (1) year warranty on the shell, cord & motor (as seen below). WARRANTIES ARE ONLY VALID WITH A PROOF OF PURCHASE (i.e.: invoice or sales order). This warranty does not cover product damage due to abuse, excessive wear or damage due to the owner not providing the necessary care (i.e.: a tangled mess of a power cord which is shorting out due to improper wrapping).

All return merchandise for credit (no older than 30 days from proof of purchase) will be subject to inspection and be charged an 18% restocking fee. Power Vac will not be responsible for return shipping charges.



A warranty card is included with the purchase of a new vacuum. Please fill it out and return in a timely manner.